

Quick Start Guide

For a full manual of the UBI5000E, please visit our website at http://www.globaltrackinggroup.com/company_support.cfm

Welcome to Global Tracking Group. With a few quick and simple steps you will be using your new UBI5000E for real time gps tracking. Just follow the instructions below for fast setup or visit our website at http://www.globaltrackinggroup.com/company_support.cfm for a full UBI5000E manual.

Getting Started

Often times your UBI5000E will come fully charged. To check the charge level, plug in the UBI500E and if the battery light **6** goes solid after 3 minutes, it is fully charged. If it flashes fast, it is in need of charging and let it continue to charge until it turns solid. After charging is complete, if you haven't already done so, use the link on the automated email you received after completing the sale to create your username and password for access to the mapping application. Your password should be at least 8 characters and contain alpha-numeric characters.

- 1 On/Off:** By holding this button for 3 seconds the UBI5000E will turn on. Hold again for 3 seconds to turn off.
Note: When charging the unit, power will turn on. Turn your unit OFF when charging is complete. Do not charge overnight. When blue light is solid remove the charger.

- 2 Power port/Antenna:** When needing to charge the UBI5000E, use this mini USB port with the included wall charger.

- 3 SIM Slot:** SIM card for sending GPS fix data to Global Tracking Group mapping application.

- 4 SOS:** Hold this button for 3 seconds and an SOS alert will be sent to the preconfigured email addresses or phone number for SMS messages in the GTG mapping tool. (see full instructions for setting up)

5 GPS Led:

GPS has satellite fix	Solid
GPS is in fixing to the satellites	Fast flash
GPS is on and GPS data wrong	Slow flash
GPS is off	No lights

6 Battery Led:

Power on and normal	No lights
Charger Inserted and charging completed	Solid
Charger inserted and charging	Fast Flash
Power key was pressed and preparing to power off	Fast Flash
Power low alert	Slow Flash
Power off or turn off the power light by command	No lights

7 GSM Led:

Searching for GSM network	Fast flash
Network has been found	Slow flash
Power off	No lights

